



MEMEX YASNAC MX3/LX3 MEMORY INSTALLATION MANUAL



M100719E
January 2007

Memex Automation Inc.
777 Walkers Line
Burlington, Ontario Canada L7N 2G1
Phone: 905-635-3040 Fax: 905-631-9640
Internet: <http://www.memex.ca>

© 2007 Memex Automation Inc. All Rights Reserved.

Yasnac is a trademark of Yaskawa Ltd. All other brand names and models mentioned in this manual are for reference only and are considered to be trademarks or registered trademarks of their respective owners. Memex assumes no liability for the use of this manual.

CHAPTER 1: INTRODUCTION

The Yasnac MX-3 CNC has two distinct memory boards. All system data including Tool Offsets and Parameters are stored in the MM20 memory board. Part-Program data is stored in the MM21-X memory board. The MM21 board is plugged into the control's Masterboard JANCD-MB20E at the position labeled "CND". It is the third board to the left of the Power Supply module.

The available Yasnac original memory boards are as follows:

<u>BOARD</u>	<u>MEMORY OPTION SIZE</u>
MM20	20M, 8k, 66 feet of tape
MM20	40M, 16k, 131 feet of tape
MM21-1	80M, 32k, 262 feet of tape
MM21-2	160M, 64k, 492 feet of tape
MM21-3	320M, 128k, 1049 feet of tape
MM21-4	640M, 256k, 2099 feet of tape
MM21-5	1280M, 512k, 4199 feet of tape
MM21-6	2560M, 1024, 8399 feet of tape (1 Megabyte) = our MX-3



A Yasnac MX3 Control

CHAPTER 2: BACKUP YOUR CONTROL

Before starting the installation, power on the control and verify that the machine tool is in good working order. If the control has a system error, or the memory is inoperable, you will have to replace your memory board with the new MX-3 memory, and restore the information from existing backup sources.

Important!

Check and backup if necessary the following memory contents: NC parameters, Diagnostic Tooling information, Tool Offsets, and Part Programs (if needed). In upgrading the Part Program memory with our MX-3 memory board, only the part programs need to be backed up - although it is recommended that a full backup of all the control's data be backed-up. If you have an existing smaller MM21 board and it is removed from the control, it will only retain the Part Program data for about 20 minutes. For this reason, it is essential that the Part-Programs be backed up properly on the computer via the RS-232 serial port. Use the following procedures to save the data on a computer. If in doubt, consult your Yasnac manuals, as they are your ultimate authority on your particular version of control.

1. Set up your computer to receive data through its COM port and connect it to your Yasnac control. Set the communication parameters on your PC for 7 data bits, and the stop bits and baud rate as determined by the applicable parameters for your control. Please refer to the "Yasnac MX3 Technical Summary" section in the back of this manual for the appropriate parameters.

NC Parameters

2. Make the computer ready to receive the data.
 - Select EDIT Mode.
 - Press the **PRM** key to display the Parameter Screen.
 - Press **RESET** **OUT**

The Parameters will be punched out.

Part Programs

3. Make the computer ready to receive the data.
 - Select EDIT Mode.
 - Press **PROG** to display the Program Screen.
 - Press **RESET** **O** **-** **9** **9** **9** **9** **OUT**

All of the programs will be punched out. Please check this.

Note: If you have any macro programs (O9000 series), you will need to check that they have also been punched at this time.

Check that parameter #6021.7= 0 and bit 3 =1 to get the O9000s to be unprotected and punchable (e.g. #6021 = 0xxx 1xxx).

Unprotect the O8000 files (if applicable) by setting parameter #6004 = xxx0 0xxx.

You will need to set Parameter Write Enable parameter #6219=4 to enable parameter writing by the way.

Tool Offsets

4. Make the computer ready to receive the Tool Offset data.
 - Confirm that EDIT Mode is selected.
 - Press **OFS** to display the Tool Offset Screen.
 - Press **RESET** **OUT**

The Tool Offsets will be punched out.

Tooling Data

5. Write down the Tooling Data from the Diagnostic Screen. Record parameters between, and including the following: 8600 - 8700
 - Press the **DGN** key to display the Diagnostic Parameter Screen.
 - You can use the **↓** (cursor) key to advance the Diagnostic number.
 - Write down the Diagnostic values.
 - Repeat the last two lines to record the remaining diagnostics.

CHAPTER 3: YASNAC MX-3 INSTALLATION PROCEDURE

Time Needed:	About 1 hour
Tools Needed:	1 Philips Screwdriver 1 Small Slot Screwdriver
Components:	1 Memex MX-3 memory board 1 Set of Instructions
Controls:	Yasnac MX-3, LX-3


Important!


1. Before starting the installation, power on the control and verify that the machine tool is in good working order.
2. Make sure that you have a current backup of the NC parameters, Tool Offsets and Part Programs. For instructions on downloading your control's information, refer to Chapter 2 entitled "Backup Your Control" in this manual.
3. Enable the secure parameters.
 - Select MDI Mode.
 - Press the **SET** key to display the Settings Screen.
 - Use the **↓** (page down) key to display Parameter P6219.
 - Enter **4** then **WR** to enable the parameters.
4. Check REGEN enable parameter P6047 as bits 7, 2 and 1 must be on (the parameter should look like "1xxx x11x" where "x" is the original value). Keep notes of all bits changed of course. (NB: Use INSERT key to change bits above.)
5. Enable the new memory.
 - Press the **PRM** key to display the Parameters Screen.
 - Press the **↓** (page down) key to display Parameter P6041 for an MX3 Mill or P6039 for an LX3 Lathe.
 - Press the **INSERT** to edit P6041 (or P6039), then use the **↓** (cursor) key to select the appropriate bits.
 - Enter a **1** or a **0** , then **WR** to set D3, D2, D1, D0 to 0111.

- Press the **INSERT** to finish editing P6041 or P6039.
6. Protect the secure parameters.
 - Press the **SET** key to display the Settings Screen.
 - Use the **↓** (page down) key to display Parameter P6219.
 - Enter **0** then **WR** to protect the parameters (or leave it the way it was in the beginning).
 7. Inspect the Memex MX-3 memory board for any damage during that may have occurred during shipping.
 8. With the Yasnac control powered off and the Emergency Stop (E-STOP) button depressed, gain access to the main masterboard. Find the MM21 memory board on the masterboard, and carefully remove it with a Philips screwdriver. Carefully place the old MM21 board in the anti-static box supplied, and set it aside.
 9. Install the MX3 in the MM21 slot (to the left of the MM20 board) and if necessary, remove the existing smaller MM21 board using a Philips screwdriver.

Remove the MM21 memory.

Install the MX3 memory.






10. Locate the Rotary Switch on the upper left of the masterboard. Turn the switch to position “7” with a small screwdriver.

11. Power on the control. This will cause the control to start-up into its GENERATION screen. If the control will not power on at this point, check that the cabinet door interlock is bypassed.

12. On the GENERATION screen press **RESET** **NEXT** then **PROG** and wait for the GENERATION COMPLETE message (about 4 sec). You should see a “2560M (or 1280M) Created” message. Power off.



13. Restore the Rotary Switch to position 0. Close the electrical cabinet then power on the control.

14. Erase the new memory and initialize the directory.

- Select EDIT Mode.
- Be sure the Memory Protect Key is set.
- Press **PROG** to show the Program Screen.
- Press **INSERT** **O** **-** **9** **9** **9** **9** **ERASE** to clear the new memory.

15. Check the Directory to verify free memory for 2560M you should see about 1 Megabytes available.

16. Reload the Part-Program data:

EDIT, PROG, RESET, O-9999, IN (IN flashes while loading)

- Re-Protect the O9000 files again if desired
(Set parameter #6021= 1xxx 0xxx where x =original value)
- Re-Protect the O8000 files again by setting parameter #6004 = xxx1 1xxx, where x = original value.

17. Reset REGEN enable parameter P6047 as bits 7, 2 and 1 to off (the parameter should look like “0xxx x00x” where “x” is the original

value). Keep notes of all bits changed of course. (NB: Use INSERT key to change bits above.)

18. Congratulations – you have now successfully installed a Memex MX-3 Yasnac memory upgrade. Thank you for going with Memex Automation - we appreciate your business.



An installed Memex MX3 Board in the MM21 slot beside the MM20 Board.

MX-3 INSTALLATION CHECKLIST (for Yasnac MX-3 Controls)

- Check Machine - Power On - Check for Machine Problems Before You Start.
- To View the Directory: Go to the ALARM screen, PAGE DOWN twice.
- Check that O9000 Part Programs are not protected – unprotected if so (#6021 = 0xxx 1xxx) & O8000 (#6004 = xxx0 0xxx)
- To Download Part Programs: EDIT mode, PROG, RESET, O-9999, OUT
- To Download Tool Offsets: EDIT mode, OFS, RESET, OUT
- To Download Parameters: EDIT mode, PRM, RESET, OUT
- Power Off
- Replace Memory Board
- Turn rotary switch to 7
- Power On
- Push RESET, NEXT, PROG to format memory.
- Power Off
- Turn rotary switch back to 0
- Power On
- Enable the new memory:
 - Change P6219 = 4: MDI, SET, Pg. Dn. to P6219, 4, WR
 - Check that P6047 = “1xxx x11x”
 - Change P6041 or P6039: PRM, P6041 or P6039, INSERT, CURSR, enter 1 or 0, WR, INSERT
 - Reset P6219 = 0: SET, Page Down to P6219, 0, WR
- Erase memory: EDIT, KEY, PROG, INSERT, O-9999, ERASE
- Check the Directory to verify free memory (1047748 for 2560M):
- Reload the Part-Program data: EDIT, PROG, RESET, O-9999, IN (IN flashes while loading)
- Re-Protect O9000 macro files if necessary (#6021 = 1xxx 0xxx) & O8000 (#6004 = xxx1 1xxx)
- Reset REGEN enable parameter P6047 = “0xxx x00x” where “x” is the original value (if “0” bits 7/2/1 were a 1 set them back to their original value.
- Complete.

CHAPTER 4: Yasnac MX3 Technical Summary

Communication settings:

Check the Input Device:

	<i>Input Device 1</i>	<i>Input Device 0</i>
RS-232 Interface 1	Parameter 6003, D1 = 0	Parameter 6003, D0 = 1
RS-232 Interface 2	Parameter 6003, D1 = 1	Parameter 6003, D0 = 0


Check the Output Device:

	<i>Output Device 1</i>	<i>Output Device 0</i>
RS-232 Interface 1	Parameter 6003, D5 = 0	Parameter 6003, D4 = 1
RS-232 Interface 2	Parameter 6003, D5 = 1	Parameter 6003, D4 = 0

Check the Port Settings:

	<i>Input Baud Rate Select</i>	<i>Output Baud Rate Select</i>
RS-232 Interface 1	Parameter 6026	Parameter 6028
RS-232 Interface 2	Parameter 6027	Parameter 6029

RS-232 Parameters 6026 – 6029 Definition: XXXXXXXX



- Parameter 6026: Settings for Input on RS-232 Interface 1
- Parameter 6027: Settings for Input on RS-232 Interface 2
- Parameter 6028: Settings for Output on RS-232 Interface 1
- Parameter 6029: Settings for Output on RS-232 Interface 2

Baud Rate Chart:

Baud	Bit 3 – D3	Bit 2 – D2	Bit 1 – D1	Bit 0 – D0
50	0	0	0	0
100	0	0	0	1
110	0	0	1	0
150	0	0	1	1
200	0	1	0	0
300	0	1	0	1
600	0	1	1	0
1200	0	1	1	1
2400	1	0	0	0
4800	1	0	0	1
9600	1	0	1	0

Notes:

- Note that if you have soft keys and have trouble loading larger files into the memory (greater than 32k), it may be the sub function editing option related problem - check parameter 6076 bit 4 and set it to a 1 to enable normal editing functionality.



Memex Automation Inc.
777 Walkers Line
Burlington, Ontario
Canada L7N 2G1
Phone: 905-635-3040 Fax: 905-631-9640
www.memex.ca

Manufacturing Connectivity Solutions™

Thank you for using Memex products.

File: ISO9000\DOCs\M100719E- Mx3 for Yasnac Manual.doc